

A-ES800 Series Fingerprint Cabinet Lock

User Manual

Version 1.2

Product Specifications

- Unlocking Method: Fingerprint
- User Capacity: 20 Fingerprints
- Power Supply: 3×AAA Alkaline Batteries
- Standby Duration: More than 1 Year
- Working Current: <50mA
- Emergency Power Supply: Type-C USB
- Working Temperature: -20°C ~ 60°C
- Humidity: 20%~85% (Non-condensing)
- ESD Protection: Contact $\pm 8KV$, Air $\pm 15KV$
- Application: Wardrobe, Cabinet, Drawer, Bedside Table, Shoe Cabinet

1、LED Indicator Description

- Factory Demo Mode: Blue Light Flashes
- Verify Success: Green Light Flashes
- Verify Failed: Red Light Flashes 3 Times
- Low Battery: Green & Red Light Flash 3 Times

2、Fingerprint Registration

- Place finger on sensor until green light on, then lift up.
- Repeat pressing the same finger 10 times, green light stop → 1st fingerprint registered.
- Blue light on, register second finger 10 times → 2nd fingerprint completed.
- Note: Slightly change finger angle during enrollment for higher recognition rate.

3、Add New Fingerprint

- Verify any registered fingerprint.
- Keep pressing until blue-green light lights up, then release.
- Press new finger 10 times steadily → new fingerprint added successfully.
- Morse Emergency Password Function

4. Factory Reset

- Unlock with valid fingerprint.
- Long press sensor until white light on, continue hold until red & green light on.
- Release finger, system restore factory settings (all fingerprints cleared).

5. Set 2-Digit Emergency Password

- Unlock fingerprint, long press until white light on then release.
- Green light: Press fingerprint for N times (1st digit).
- Blue light: Press fingerprint for M times (2nd digit).
- Example: Press 5 times + 6 times = Password 56

6. Emergency Unlock

- Long press any position until white light flash, release.
- Green light: Input first digit pressing times.
- Blue light: Input second digit pressing times.
- Red flash: Password wrong
- Green flash: Unlock success and auto restore factory

7. Password Remark

- Default password: 33
- Factory reset will restore default password
- Operation overtime will automatically exit

8. online video tutorial

- Please use your mobile phone to scan the QR code to view the online video tutorial.



SA-ES805 User Manual